

Fitness Entertainment

900MHz Analog Wireless Receiver

ARG's 900MHz systems feature easy to select, Wi-Fi friendly frequencies with up to a 400 foot transmission range (Line of site). These systems provide additional flexibility for users to locate multiple interference-free channels, regardless of location or environment. Our 900MHz wireless receiver (ARG-CV-900AR) is durable, compact and easy to install and operate. ARG's 900MHz systems provide long lasting, robust performance at cost-conscious pricing and are compatible with all other manufacturer's 900MHz products.



ARG-CV-900AR Technical Specifications

Dimensions:	4.06" H x 2.68" W x 1.30" D
Weight:	3.21 Oz
Color:	Black
Features:	Lightweight, compact design Easy to install Compatible with all other manufacturers 900MHz products Auto scan function for memorizing available frequencies Headphone jack insert power on/off Replaceable durable headphone jacks with replacement alert
Display:	Green LCD Display
Frequency Range:	902.00MHz - 927.95MHz
Frequency Spacing:	50 KHz
Frequency Response:	50 Hz - 15 KHz
Audio Sampling:	Analog
Signal to Noise Ratio:	60 dB
Current Draw:	DC3.7V 45mA
Audio Input:	Analog Line In, Digital coaxial and digital optical
Transmission Method:	FM
Transmission Range:	400 Ft Line of Site
Warranty:	2 years parts
FCC Certification:	This device complies with Part 15 of the FCC rules. Operation is subject to 1) this device may not cause harmful interference and 2) this device must accept interference received, including interference that may cause undesired operation. FCC Regulations section 15.21 requires the user to comply with the rules of transmitter operation. Any changes or modifications made by the user not expressly approved for compliance may result in the loss of all privileges and authority to operate the equipment.

NOTE: SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE!

405 Main Ave W Unit 4G, West Fargo, ND 58078 • (P) 888-468-4552 • (F) 888-373-4819
 info@argaudio.com • www.argaudio.com